

TECHNICAL DATA

Fluke 9040 Phase Rotation Indicator



Key features

- 3 phase indication
- Indication of phase rotation
- Clear LCD display
- No battery required

Product overview: Fluke 9040 Phase Rotation Indicator

Phase rotation indicator with high voltage capability for industrial applications

The Fluke 9040 is effective for measuring phase rotation in all areas where three phase supplies are used to feed motors, drives and electrical systems. The Fluke 9040 is a rotary field indicator and can provide clear indication of the 3 phase via an LCD display and the phase rotation direction to determine correct connections. It allows rapid determination of phase sequence and has a voltage (up to 700 V) and frequency range suitable for commercial and industrial applications. The included test probes have a variable clamping range for safe contact, also in industrial sockets.

Specifications: Fluke 9040 Phase Rotation Indicator

Technical Specifications	
Voltage Range	40-700 V
Frequency Range	15-400 Hz
Operating Timer	Continuous
Environmental Specifications	
Operating Temperature	0°C to 40°C
Dust/Water Resistance	IP 40
Safety Specifications	
Electrical Safety	EN 61010,
	EN 61557-7
Overvoltage category	CAT III, 600 V
	CAT IV, 300V
Mechanical and General Specifications	
Size	124 x 61 x 27 mm
Weight	200 g
Power supply	From unit under test
Warranty	2 years

Ordering information



Fluke 9040

Fluke 9040 Phase Rotation Indicator

Includes:

- 3 self-retaining test probes (black)
 - alligator clip
 - user manual
-

Fluke. *Keeping your world up and running.®*

Fluke Corporation

PO Box 9090, Everett, WA 98206 U.S.A.

For more information call:

In the U.S.A. (800) 443-5853

In Europe/M-East/Africa +31 (0)40 267 5100

In Canada (800)-36-FLUKE

From other countries +1 (425) 446-5500

Fluke Electronics (Malaysia) Sdn Bhd

Suite D-3A-4, Block D

SouthGage Commercial Centre, No2

Jalan Dua Off Jln Chan Sow Lin

55200 KL

Malaysia

Email: info.asean@fluke.com

www.fluke.com/my

©2026 Fluke Corporation. Specifications subject to change without notice.

03/2026

Modification of this document is not permitted without written permission from Fluke Corporation.